

# **Edixeon<sup>®</sup> ARC Series**

Edixeon® ARC series emitters are one of the high power LEDs packaged by Edison-Opto delivering high luminous flux in the world. With its advanced packaging process, Edixeon® ARC is introduced to satisfy various solid-state lighting application such as automotive headlamp, decorative wall washer and general lighting. Edixeon® ARC series emitters have a typical luminous output of 100 lumens at 350mA, and are built specifically for reflow process. Unlike most fluorescent sources, Edixeon® ARC series contains no mercury and is more energy efficient than incandescent and halogen light source.

#### **Features**

- Various colors
- More energy efficient than incandescent and most halogen lamps
- Low voltage operation
- Instant light
- Long operating life
- Reflow process compatible



# **Table of Contents**

Product Nomenclature	2
Environmental Compliance	3
LED Package Dimensions and Polarity	4
LED Package with Star Dimensions and Polarity	5
Absolute Maximum Ratings	6
Luminous Flux Characteristics	7
Forward Voltage Characteristics	9
JEDEC Information	10
Reliability Items and Failure Measures	11
Color Spectrum and Radiation Pattern	12
Optical & Electrical Characteristics	16
Product Soldering Instructions	21
Product Thermal Application Information	25
Product Electrical Application Information	30
Emitter Product Packaging Information	31
Star Product Packaging Information	33



## **Product Nomenclature**

The following table describes the available color, power, and lens type. For more flux and forward voltage information, please consult the Bin Group document.

< Table 1 Edixeon® ARC series nomenclature >






# **Environmental Compliance**

Edixeon® ARC series are compliant to the Restriction of Hazardous Substances Directive or RoHS. The restricted materials including lead, mercury cadmium hexavalent chromium, polybrominated biphenyls (PBB) and polybrominated diphenyl ether (PBDE) are not used in Edixeon® ARC series to provide an environmentally friendly product to the customers.



# **LED Package Dimensions and Polarity**



< Figure 1 Edixeon<sup>®</sup> ARC series dimensions >


#### Notes:


- 1. All dimensions are measured in mm.
- 2. Drawings are not to scale.
- 3. It is strongly recommended to apply on electrically isolated heat conducting film between the slug and contact surfaces.



# **LED Package with Star Dimensions and Polarity**


## EDSx-xLSx-xx-Ax16






# EDSx-xLSx-xx-Bx16

# Side View



# EDSx-xLSx-xx-Cx16



<Figure 2 Edixeon® star dimensions>

#### Notes:

1.All Dimensions are in mm.



## **Absolute Maximum Ratings**

The following tables describe the characteristics of Edixeon® ARC series under various current.

< Table 2 Absolute maximum ratings for Edixeon® ARC series >

Parameter	Rating(1W)	Rating(3W)	Unit	Symbol
DC Forward Current(1W)	350	700	mA	I <sub>F</sub>
Peak pulse current;(tp≤100µs, Duty cycle=0.25)	500	1,000	mA	
Reverse Voltage	5	5	V	$V_{R}$
Drive Voltage	7	7	V	V <sub>D</sub>
LED junction Temperature	125	125	$^{\circ}$	Tj
Operating Temperature	-30 ~ +110	-30 ~ +110	$^{\circ}$	
Storage Temperature	-40 ~ +120	-40 ~ +120	$^{\circ}$	
Soldering Temperature	260	260	°C	
ESD Sensitivity	4,000	4,000	V	V <sub>B</sub>
Manual Soldering Time at 260°C (Max.)	5	5	Sec.	

#### Notes:

- 1. Proper current derating must be observed to maintain junction temperature below the maximum at all time.
- 2. LEDs are not designed to be driven in reverse bias.
- 3. Allowable reflow cycles are 3 times for each LED.
- 4. tp: Pulse width time

The following tables describe thermal resistance of Edixeon<sup>®</sup> ARC series under various current and different color.

< Table 3 Temperature Coefficient of Forward Voltage & Thermal Resistance Junction to Case Characteristics at Tj=25°C for Edixeon® ARC series >

Part Name	Color	△V	r/△T	Re.	J-B
r art Hame	00101	Тур.	Units	Тур.	Unit
EDEx-1LSx		-2	mV/℃	13	°C/W
EDEx-3LSx		-2	mV/℃	13	°C/W



# **Luminous Flux Characteristics**

The following tables describe flux of Edixeon® ARC series under various current and different color.

Part Name	art Name Color Flux			Unit	
rait Name	Coloi	Min.	Тур.	Max.	Onne
EDEW-1LS1	Cool White	55.0	75.0		lm
EDEW-1LS5-B1	Cool White	80.0	100.0		lm
EDEH-1LS1-E1	Neutral White	45.0	55.0		lm
EDEH-1LS5-E1	Neutral White	60.0	80.0		lm
EDEX-1LS1-E1	Warm White	40.0	45.0		lm
EDEX-1LS5-E1	Warm White	50.0	65.0		lm
EDEW-1LS5-D1	Cool White	30.3	45.0		lm
EDEH-1LS5-D1	Neutral White	23.3	35.0		lm
EDEX-1LS5-D1	Warm White	23.3	30.0		lm

Part Name	Color		Flux		Unit
rait Naille	Coloi	Min.	Тур.	Max.	Offit
EDEW-3LS5-B3	Cool White	120.0	170.0		lm
EDEH-3LS5-E3	Neutral White	90.0	100.0		lm
EDEX-3LS5-E3	Warm White	80.0	90.0		lm
EDEW-3LS5-D3	Cool White	51.2	70.0		lm
EDEH-3LS5-D3	Neutral White	39.4	60.0		lm
EDEX-3LS5-D3	Warm White	39.4	55.0		lm

#### Notes:

- 1. Flux is measured with an accuracy of  $\pm$  10%.
- 2. Cool white neutral white warm white emitters are built with InGaN



< Table 6 Edixeon® ARC series photometric luminous flux group for 1W & 3W >

Group	Min.	Max.
R	39.4	51.2
S1	51.2	58.8
S2	58.8	66.5
T1	66.5	70.0
T2	70.0	80.0
Т3	80.0	86.5
U1	86.5	90.0
U2	90.0	100.0
U3	100.0	112.5
V	112.5	146.2
W	146.2	190.0
Χ	190.0	247.1
Υ	247.1	321.2
Z	321.2	417.5



# **Forward Voltage Characteristics**

The following tables describe forward voltage of Edixeon® ARC series emitter under various current.

< Table 7 Forward voltage characteristics at  $I_F$ =350mA and  $T_J$ =25 $^{\circ}$ C for 1W Edixeon $^{\otimes}$  ARC series >

Part Name	Color	V <sub>F</sub>	Unit	
rait Naille	Coloi	Min.	Max.	Offit
EDEW-1LS1	Cool White	3.1	4.0	V
EDEW-1LS5-x1	Cool White	3.1	4.0	V
EDEH-1LS5-x1	Neutral White	3.1	4.0	V
EDEX-1LS5-x1	Warm Whit	3.1	4.0	V

< Table 8 Forward voltage characteristics at IF=700mA and TJ=25°C for 3W Edixeon® ARC series >

Part Name	Color	V <sub>I</sub>	=	Unit
rait Name	60101	Min.	Max.	Offit
EDEW-3LS5-x3	Cool White	3.1	4.3	V
EDEH-3LS5-x3	Neutral White	3.1	4.3	V
EDEX-3LS5-x3	Warm White	3.1	4.3	V



#### **JEDEC Information**

JEDEC moisture sensitivity classification is used to determine what classification level should be used for initial reliability qualification. Once identified, the LEDs can be properly packaged, stored and handled to avoid subsequent thermal and mechanical damage during the assembly solder reflow attachment and/or repair operation. The present moisture sensitivity standard contains six levels, the lower the level ,the longer the devices floor life. Edixeon<sup>®</sup> ARC series are certified at level 2a. This means Edixeon<sup>®</sup> ARC series have a floor life of 4 weeks before Edixeon<sup>®</sup> ARC series need to re-baked.

< Table 9 JEDEC characteristics at T<sub>J</sub>=25°C for Edixeon® ARC series>

	Soak Requir					nts	
	Flo	or Life			Acc	elerated Equiv	/alent
Level			Standard Time(hours) Condition		eV	eV	
					0.40~0.48	0.30~0.39	Condition
	Time	Condition			Time(hours)	Time(hours)	
4	72 hours	≦30°C/60% RH	96 <sup>1</sup> +5/-0	30°C/60% RH	20 +5/-0	24 +5/-0	60°C/60% RH

				So	ak Requireme	ents	
	Flo	or Life				elerated Equiv	/alent
Level	. 1357 2110		Standard		eV 0.40~0.48	eV 0.30~0.39	Condition
	Time	Condition	Time(hours)	Condition	Time(hours)	Time(hours)	
1	Unlimited	≦30°C/85% RH	168 +5/-0	85°C/85% RH	NA	NA	NA
2	1 year	≦30°C/60% RH	168 +5/-0	85℃/60% RH	NA	NA	NA
2a	4 weeks	≦30°C/60% RH	696 <sup>1</sup> +5/-0	30°C/60% RH	120 +1/-0	168 +1/-0	60°C/60% RH
3	168 hours	≦30°C/60% RH	192 <sup>1</sup> +5/-0	30°C/60% RH	40 +5/-0	52 +5/-0	60°C/60% RH
4	72 hours	≦30°C/60% RH	96 <sup>1</sup> +5/-0	30°C/60% RH	20 +5/-0	24 +5/-0	60°C/60% RH
5	48 hours	≦30°C/60% RH	72 <sup>1</sup> +5/-0	30°C/60% RH	15 +5/-0	20 +5/-0	60°C/60% RH
5a	24 hours	≦30°C/60% RH	48 <sup>1</sup> +5/-0	30°C/60% RH	10 +5/-0	13 +5/-0	60°C/60% RH
6	Time on label (TOL)	≦30°C/60% RH	TOL	30°C/60% RH	NA	NA	NA

#### Notes:

- The standard soak time includes a default value of 24 hours for semiconductor manufacturer's exposure time (MET) between bake and bag, and includes the maximum time allowed out of the bag at the distributor's facility.
- Joint Electron Devices Engineering Councils (JEDEC) is the leading developer of standards for the solid-state industry. Almost 3100 participants, appointed by some 290 companies work together in 50 JEDEC committees to meet the needs of every segment of the industry, manufacturers and consumers alike. The publications and standards that they generate are accepted throughout the world. (http://www.jedec.org)



## **Reliability Items and Failure Measures**

#### Reliability test

The following table describes operating life, mechanical, and environmental tests performed on Edixeon<sup>®</sup> ARC series package.

< Table 10 Operating life, mechanical, and environmental characteristics and  $T_J=25^{\circ}C\ for$  Edixeon<sup>®</sup> ARC series>

Stress Test	Stress Conditions	Stress Duration	Failure Criteria
Room Temperature Operating Life	$25^{\circ}$ C, $I_F = I_F$ Max DC (Note 1)	1,000 hours	Note 2
High Temperature High Humidity Storage Life	85℃ / 85%RH	1,000 hours	Note 2
High Temperature Storage Life	110℃	1,000 hours	Note 2
Low Temperature Storage Life	-40℃	1,000 hours	Note 2
Thermal Shock	-40 / 125 $^{\circ}$ C, 15 min dwell /<10 sec transfer	500 cycles	No catastrophics
Mechanical Shock	1500 G, 0.5 msec pulse, 5 shocks each of 6 axis		No catastrophics
Natural Drop	On concrete from 1.2 m, 3X		No catastrophics
Variable Vibration Frequency	10-2000-10 Hz, log or linear sweep rate, 20 G about 1 min, 1.5 mm, 3X/axis		No catastrophics
Solder Heat Resistance (SHR)	260°C ± 5°C, 10 sec		No catastrophics

#### Notes:

- 1. Depending on the maximum derating curve.
- Failure Criteria:

Electrical failures

 $V_F$  shift >=10%

Light Output Degradation

% lv shift >= 30% @1,000hrs or 200cycle

Visual failures


Broken or damaged package or lead

Solderability < 95% wetting


Dimensions out of tolerance



# **Color Spectrum and Radiation Pattern**




<Figure 3. Cool white color spectrum at  $T_J$  =25  $^\circ\! {\rm C}$  .for Edixeon  $^{\! B}$  ARC series >




< Figure 4. Neutral White  $\,^{^{\circ}}$  Warm white color spectrum at  $T_J$  =25  $^{\circ}$ C .for Edixeon  $^{^{\otimes}}$  ARC series >






< Figure 5. Cool white color spectrum at  $T_J$  =25 $^{\circ}$ C .for Edixeon<sup>®</sup> ARC series EDEW-xLS5-Dx >




< Figure 6.Neutral white color spectrum at  $T_J$  =25 $^{\circ}$ C .for Edixeon $^{\otimes}$  ARC series EDEH-xLS5-Dx>





< Figure 7. Warm white color spectrum at  $T_J$  =25 $^{\circ}$ C.for Edixeon $^{\oplus}$  ARC series EDEX-xLS5-Dx >



<Figure 8.Lambertain at TJ=25°C for Cool White · Neutral White · Warm white.>



## **Emission Angle Characteristics**

< Table 11 Emission angle Characteristics at Tj=25°C for Edixeon® ARC series >

Part Name	Color	2Θ½(Typ.) Lambertian	Unit
EDEW-xLS5-xx	Cool White	130	Deg.
EDEH-xLS5-xx	Neutral White	130	Deg.
EDEX-xLS5-xx	Warm White	130	Deg.

#### Notes:

1. Emission is measured with an accuracy of  $\pm$  10 Degree.

## **Color Temperature Characteristics T**<sub>J</sub>=25℃

< Table 12 Color Temperature Characteristics at Tj=25°C for Edixeon® ARC series >

Part Name	Name Color CCT		Unit	
rait Naine	Coloi	Min.	Max.	Offic
EDEW-xLS5-xx	Cool White	5,000	10,000	K
EDEH-xLS5-xx	Neutral White	3,800	5,000	К
EDEX-xLS5-xx	Warm White	2,670	3,800	К

#### Notes:

1. CCT is measured with an accuracy of ± 200K

## **Color Temperature Characteristics T**<sub>J</sub>=25℃

< Table 13 Color Rendering Index Characteristics at Tj=25°C for Edixeon® ARC series >


Part Name	Color	CRI
rait Naille	Coloi	Тур
EDEW-xLS5-Bx	Cool White	65
EDEH-xLS5-Ex	Neutral White	75
EDEX-xLS5-Ex	Warm White	75
EDEW-xLS5-Dx	Cool White	90
EDEH-xLS5-Dx	Neutral White	90
EDEX-xLS5-Dx	Warm White	90

#### Notes:


1. CRI is measured with an accuracy of ± 5



# **Optical & Electrical Characteristics**




< Figure 9 Operating Current & Ambient Temperature for 1W Edixeon® ARC series>




< Figure 10 Operating Current & Ambient Temperature for 3W Edixeon® ARC series >






< Figure 11 Forward Current & Forward Voltage at T<sub>J</sub>=25°C for 1W Edixeon® ARC series >




< Figure 12 Forward Current & Forward Voltage at T<sub>J</sub>=25°C for 3W Edixeon® ARC series >






< Figure 13 Forward Current & Relative Luminous at  $T_J$ =25 $^{\circ}$ C for 1W Edixeon<sup>®</sup> ARC series>




< Figure 14 Forward Current & Relative Luminous at TJ=25°C for 3W Edixeon® ARC series>






< Figure 15.Forward Current & CCT at TJ=25°C for Edixeon® ARC series Cool White>




< Figure 16.Forward Current & CCT at TJ=25°C for Edixeon® ARC series Neutral White>





< Figure 17.Forward Current & CCT at TJ=25°C for Edixeon® ARC series Warm White>




< Figure 18. Junction temperature & power rate for Edixeon® ARC series >



# **Product Soldering Instructions**

The central circle pad at the bottom face of the package provides the main path for heat dissipation from the LED to the heat sink (heat sink contact).



The choice of solder and the application method will dictate the specific amount of solder. For most consistent results, an automated dispensing system or a solder stencil printer is recommended.

Positive results will be used solder thickness that results in 50µm. The lamp can be placed on the PCB simultaneously with any other required SMD and reflow completed in a single step. Automated pick-and-place tools are recommended.

The central slug at the bottom face of the package provides the main path for heat dissipation from the LED to the heat sink (heat sink contact). A key feature of Edixeon® ARC series is an electrically neutral heat path that is separate from the LED's electrical contacts. This electrically isolated thermal pad makes Edixeon® ARC series perfect for use with either FR4 circuit boards with thermal via or with metal-core printed circuit boards (MCPCB).



#### **Recommend Solder Steps**

To prevent mechanical failure of LEDs in the soldering process, a carefully controlled pre-heat and post-cooling sequence is necessary. The heating rate in an IR furnace depends on the absorption coefficients of the material surfaces and on the ratio of the component's mass to its irradiated surface. The temperature of parts in an IR furnace, with a mixture of radiation and convection, cannot be determined in advance. Temperature measurement may be performed by measuring the temperature of a

Temperature measurement may be performed by measuring the temperature of a specific component while it is being transported through the furnace. Influencing parameters on the internal temperature of the component are as follows:


- Time and power
- Mass of the component (for Edixeon® ARC series on MCPCB)
- Size of the component
- · Size of the printed circuit board
- Absorption coefficient of the surfaces and MCPCB
- Packing density

Peak temperatures can vary greatly across the PC board during IR processes. The variables that contribute to this wide temperature range include the furnace type and the size, mass and relative location of the components on the board. Profiles must be carefully tested to determine the hottest and coolest points on the board. The hottest and coolest points should fall within the recommended temperatures. The profile of the reflow system should be based on design needs, the selected solder system and the solder-paste manufacturer's recommended reflow profile.



## **Recommended Profile for Reflow Soldering**

The following reflow soldering profiles are provided for reference. Edison recommends that users follow the recommended soldering profile provided by the manufacturer of the solder paste used.



< Figure 20 Reflow profiles >



# **Table of Classification Reflow Profiles**

## < Table 14 Reflow profiles >

Profile Feature	Sn-Pb Eutectic Assembly	Pb-Free Assembly
Preheat & Soak Temperature min (Tsmin) Temperature max (Tsmax) Time (Tsmin to Tsmax) (ts)	100 °C 150 °C 60-120 seconds	150 °C 200 °C 60-120 seconds
Average ramp-up rate (Tsmax to Tp)	3 °C/second max.	3 °C/second max.
Liquidous temperature (TL) Time at liquidous (tL)	183 °C 60-150 seconds	217 ℃ 60-150 seconds
Peak package body temperature (Tp)*	230 ℃ ~235 ℃ *	255 ℃ ~260 ℃ *
Classification temperature (Tc)	235 ℃	260 ℃
Time (tp)** within 5 °C of the specified classification temperature (Tc)	20** seconds	30** seconds
Average ramp-down rate (Tp to Tsmax)	6 °C/second max.	6 °C/second max.
Time 25 ℃ to peak temperature	6 minutes max.	8 minutes max.

<sup>\*</sup> Tolerance for peak profile temperature (Tp) is defined as a supplier minimum and a user maximum.


\*\* Tolerance for time at peak profile temperature (tp) is defined as a supplier minimum and a user maximum.



# **Product Thermal Application Information**

Thermal grease should be evenly speeded with a thickness <100um.

When assembling on MCPCB or heat sink carrier.




Edixeon® ARC series on MCPCB and heat sink

< Figure 21 Edixeon® ARC series heatsink application >

—It is strongly recommanded the heat sink should be anodized.




—Please ensure the heat sink is flat enough to prevent the bad heat conductivity.



<Figure 22 Edixeon® ARC series assemble with heatsink>



## **Thermal Resistance Application**



$$Rth_{(J-A)} = Rth_{(J-S)} + Rth_{(S-G)} + Rth_{(G-B)} + Rth_{(B-A)}$$

$$\begin{split} T_{Junction} = & T_{Ambient} + Rth_{(J-A)} \ x \ P_{Dissipation} \\ & (T_{J} = & T_{A} + Rth_{(J-A)} \ x \ P_{Dissipation}) \\ & < & Figure \ 23 \ Rth \ and \ T_{J} \ for \ Edixeon^{@} \ ARC \ series > \end{split}$$

#### Suggested Adhesive for Selection(such as thermal grease)

· Ease of use

Non-solvent, One-part

- Fast tack free
  - 3 minutes at 25°C
- No corrosion

Alcohol type of room temperature vulcanization (RTV)

Low volatility

Low weight loss of silicone volatiles

Adhesion

Excellent adhesion to most materials without use of a primer

Dielectric properties

Cured rubber exhibits good dielectric properties

Excellent thermal stability and cold resistance

Cured rubber provides wide service temperature range



< Table 15 Specification for adhesive properties >

Specification	Suggested Properties
Take-free time	3~10 minutes
Specific gravity	< 3 g/cm <sup>2</sup>
Thermal conductivity	> 2.5 W/mK
Rth in using	< 1.8 °C/W
Volume resistance	> 1x10 <sup>14</sup>
Lap shear adhesion strength	> 200 N/ cm <sup>2</sup>
Tensile strength	> 4 Mpa

#### **Thermal Resistance Calculation**

The thermal resistance between two points is defined as the ratio of the difference in temperature to the power dissipated. For calculations in the following units used are °C/W. In the case of LEDs, the resistance of two important thermal paths affects the junction temperature:

From the LED junction to the thermal contact at the bottom of the package, this thermal resistance is governed by the package design. It is referred to as the thermal resistance between junction and slug (Rth (J-S))

From the thermal contact to ambient conditions, this thermal resistance is defined by the path between the slug ,board ,and ambient. It is referred to as the thermal resistance between slug and board (Rth  $_{(S-B)}$ ) and between board and ambient (Rth  $_{(B-A)}$ ).

The overall thermal resistance between the LED junction and ambient (Rth  $_{(J-A)}$ ) can be modeled as the sum of the series resistances Rth  $_{(J-S)}$ , Rth  $_{(S-B)}$ , and Rth  $_{(B-A)}$ . The following will show how to calculate Rth for each part of LED module.

1. Rth<sub>(J-S)</sub>
Assume Edixeon<sup>®</sup> Rth<sub>(J-S)</sub>=10 °C/W

#### 2. Rth<sub>(S-G)</sub>

If the thickness of thermal grease is 100um and area is  $(6.4/2)^2\pi$  mm<sup>2</sup>. Thermal conductivity of thermal grease is 2.6 W/mK.



Therefore Rth<sub>(S-G)</sub>= 
$$\frac{100}{2.6 \text{ X } (6.4/2)^2 \pi}$$
 = 1.2 °C/W

#### 3. Rth<sub>(G-B)</sub>

The Rth of standard MCPCB is 1.5 °C/W

## 4. Rth<sub>(B-A)</sub>

The Rth between board and air is mainly dependent on the total surface area.

Therefore 
$$Rth_{(B-A)} = \frac{500}{Area(cm)^2}$$

If Area is 30cm <sup>2</sup> Rth=16.7	$Rth_{(J-A)} = 10+1.2+1.5+16.7 = 29.4  {}^{\circ}C/W$
If Area is 60cm <sup>2</sup> Rth=8.3	$Rth_{(J-A)} = 10+1.2+1.5+8.3 = 21^{\circ}C/W$
If Area is 90cm <sup>2</sup> Rth=5.5	$Rth_{(J-A)} = 10+1.2+1.5+5.5 = 18.2^{\circ}C/W$

#### **Junction Temperature Calculation**

The total power dissipated by the LED is the product of the forward voltage  $(V_F)$  and the forward current  $(I_F)$  of the LED.

The temperature of the LED junction is the sum of the ambient temperature and the product of the thermal resistance from junction to ambient and the power dissipated.

$$T_{Junction} = T_{Air} + Rth_{(J-A)} \times P_{Dissipation}$$

If one white Edixeon<sup>®</sup> in room temperature (25 $^{\circ}$ C) operated 350mA and V<sub>F</sub>=3.3V, the P<sub>Dissipation</sub>=0.35 x 3.3=1.155W

#### And junction temperature is

$$T_{Junction} = 25^{\circ}C + 18.2 \text{ x } 1.155 = 46.021^{\circ}C \text{ (total surface area = 90cm}^2)$$

$$T_{Junction} = 25^{\circ}C + 21 \times 1.155 = 49.255 {\circ}C \text{ (total surface area = 60cm}^2\text{)}$$

$$T_{Junction} = 25^{\circ}C + 29.4 \times 1.155 = 58.957 \,^{\circ}C$$
 (total surface area = 30cm<sup>2</sup>)

# Example : Junction Temperature Calculation

One white LED is used under ambient temperature ( $T_{Ambient}$ ) of 30 °C. This LED is soldered on MCPCB (Area=10cm<sup>2</sup>). Calculate junction temperature.

Assuming a forward voltage of  $V_F$ =3.3V at 350mA and total power dissipated is  $P_{Dissipation}$ =1x 0.35 x 3.3= 1.155 W.

With good design,  $Rth_{(S-G)}$  can be minimized to 1  $^{\circ}$ C /W.

 $Rth_{(G-B)}$  of a standard MCPCB can be 1.5 °C /W.



The Rth between board and air is mainly dependent on the total surface area.

Therefore it can be calculated in formula 
$$\frac{500}{\text{Area(cm)}^2}$$

$$Rth_{(B-A)} = \frac{500}{10} = 50 \text{ °C /W}.$$

Following the formula 
$$T_{Junction}$$
 = $T_{Ambient}$  + Rth<sub>(J-A)</sub> x P<sub>Dissipation</sub>   
T<sub>Junction</sub>=30 °C + (10 °C /W +1 °C /W +1.5 °C /W +50 °C /W) x 1.155W =102.1875 °C

That means this LED emitter is operated under good condition (T<sub>Junction</sub><125 ℃).


It's strongly recommended to keep the junction temperature under 125  $^{\circ}$ C Or keep the temperature of emitter lead not exceed 55  $^{\circ}$ C



## **Product Electrical Application Information**


Following graphs and descriptions show how to connect LED or LED module and plug to AC outlet.

Step1: Connect the wires of LED Module to the DC output of the driver.



<Figure 24 LED Module connect to the DC output of the driver>

Step2: Plug the driver to AC outlet.





<Figure 25 Plug the AC output of the driver to AC outlet>

Caution: Never plug the driver to AC outlet before the LED Module is properly connected as this may generate transient voltage damage the LEDs permanently with a short or open circuit.



# **Emitter Product Packaging Information**






Item	Quantity	Total	Dimensions(mm)
15"Reel	1,000pcs	1,000pcs	Diameter=380
Inner box	2 reels	2,000pcs	390*390*170
Outer box	2 inner boxes	4,000pcs	425*405*350

<Figure 26 Taping reel dimensions>






Item	Quantity	Total	Dimensions(mm)
7"Reel	200pcs	200pcs	Diameter=178
Inner box	2 reels	400pcs	240*235*67
Outer box	5 inner boxes	2,000pcs	353*254*256

<Figure 27 Taping reel dimensions>

# The Label




< Figure 28 Label on taping reel >




< Figure 29 Label on taping reel >



# **Star Product Packaging Information**



Item	Quantity	Total	Dimensions(mm)
Tray	100pcs	100pcs	325*300
Inner box	10 Tray	1,000pcs	340*330*160
Outer box	2 inner boxes	2,000pcs	350*350*340



Item	Quantity	Total	Dimensions(mm)
Tray	60pcs	60pcs	310*290
Inner box	10 Tray	600pcs	340*330*160
Outer box	2 inner boxes	1200pcs	350*350*340

<Figure 30 Edixeon® Star Package>